



STORM|AUDIO

ISR FUSION 20 - SPECIFICATIONS

	ISR Fusion 20
Main Features	Auro-3D / Dolby Atmos / DTS:X Pro / IMAX Enhanced ✓ / ✓ / ✓ / ✓ StormXT channel expander ✓ Dirac Live license included ✓ Dirac Live Active Room Treatment supporting speakers Unlimited StormMonitoring - remote monitoring ✓
Multichannel / Surround Processing	Output channels 20 Decoding / upmixing channels 20 Input sampling rate supported up to 192 kHz Post processing sampling rate 48 kHz Dirac Live runtime with high resolution mixed-phase filters ✓ Bass management : Standard & Expert ✓ Flexible bass routing (up to 6 zones, Expert mode) ✓ Multi-subwoofer channels Unlimited Multi-way crossover (6 to 48 dB/oct, Linkwitz-Riley, Butterworth) up to 4 per channel Parametric EQ per channel up to 20 filters
HDMI	HDMI inputs / outputs 7/2 Standard HDMI2.1a / HDCP2.3 ✓ Matrix capability for multi-room ✓ 8K / 4K120, rec BT709 and rec BT2020 ✓ High Dynamic Range : HDR10+ / HLG / Dolby Vision ✓ / ✓ / ✓ Color space and subsampling RGB, YCbCr, 4:4:4, 4:2:2, 4:2:0 ✓ Deep color (12 bpc) ✓ Max. resolution support (40 Gbps) 8K/4K 120fps 3D / OSD ✓ / ✓ ARC / eARC ✓ / ✓
Audio Inputs	Streaming: Roon ready end point ✓ Digital input: coaxial / optical 3 / 3 Analog stereo inputs, balanced : XLR 1 Analog stereo inputs, unbalanced: RCA 4
Audio Outputs	Analog main outputs, amplified (ch 1 to 16) 5-way binding posts Analog main outputs, balanced (ch 17 to 20) XLR Stereo downmix Zone2 outputs Digital Optical
Amplifier specifications	Max Power per channel (p-rated), 1% THD, Single Ended (SE) outputs 150W (8ohm) / 300W (4ohm) Max Power per channel, 1% THD., Bridged Tied Load (BTL) outputs (Up to 3 configurable) 500W (8ohm) / 500W (4ohm) Continous Power capability 2000W Peak Power Capability (CEA-490-A) 2500W THD+N, 5W, SE < 0.0015 % SNR, 5W, SE > 100 dB SNR, p-rated, SE > 115 dB
Set-up Management	Audio zone configuration ✓ Individual theater and zone source selection (Main & Zone2) ✓ Theater and zones listening presets Unlimited Dirac Live profiles 10 per Theater / Zone Backup and restore of set-up ✓ Firmware update via USB / network ✓ / ✓
Control Inputs / Outputs	USB type A (upgrade and monitoring) 2 Ethernet / Wi-Fi ✓ / - Output trigger control 4 (out) IR remote ports, in / out (input loop through) 1 / 1 IR remote control sensor in front panel ✓
Control / Custom Installation	Front panel display ✓ (TFT 5") Advanced control via front panel ✓ Web-based product configurator ✓ TCP/IP API based control ✓ StormRemote control application (iOS / Android) ✓ Crestron, Control4, Savant, RTI, ELAN home automation drivers ✓ Logitech Harmony IR database integration ✓ IR remote control handset ✓
Power Supply	Voltage range 100V to 240V Type SMPS Range selection Universal
Casing	Home / rack (removable ears) ✓ / ✓ Net weight (kg / lbs) 16 / 35,3 Size 4RU Dimensions - no ears, no feet (cm) 49,1 x 44,2 x 17,4 Ears : +4 cm (2 x 2 cm) - Feet : + 2 cm Dimensions - with box (cm) 62 x 54 x 30

All trademarks are the property of their respective owners. The information and product specifications contained in this datasheet are subject to change at any time without notice. StormAudio accepts no liability or responsibility for any errors or omissions in the information on this datasheet or for damages resulting from relying on the content of this datasheet.